



DESCRIPTION

PA-1C250 Compact Digital Mixer Amplifier supports USB/FM/Bluetooth with 70V/100V & 4-16Ω speaker output. It features 2 AUX inputs, 1 AUX output, and 2 MIC inputs—MIC 1 (6.3mm jack, front panel) and MIC 2 (XLR, rear panel) with phantom power. Includes individual volume control for MIC & AUX, along with bass and treble adjustments.

FEATURES

- **Built-in Functions:** Equipped with Bluetooth, USB playback for versatile audio streaming options.
- **Multiple Input/Output Options:** Features 2 MIC inputs, 2 LINE inputs, and 1 LINE output for flexible connectivity.
- **Powerful Output Capabilities:** Supports 100V or 70V constant voltage output and 4Ω–16Ω constant resistance output for adaptable installation in various environments.
- **Convenient Remote Control:** Comes with an IR remote control for easy and convenient operation from a distance.
- **Intelligent Priority Function:** Prioritizes audio sources in the following order: EMC/MIC1 > AUX1/AUX2/MIC2, ensuring critical messages are always heard.
- **Comprehensive Control:** Offers master volume control, individual MIC, and LINE volume adjustments, as well as dedicated treble and bass controls for fine-tuned audio performance.



SPECIFICATIONS

Power Supply	AC110-120V/AC220~240V 50/60Hz (Select via the switch)
MIC1 IN Sensitivity	8mV±10%
MIC2 IN Sensitivity	8mV±10%
AUX1 IN Sensitivity	350mV±10%
AUX2 IN Sensitivity	350mV±10%
EMC IN Sensitivity	350mV±10%
MIC Frequency Response	200Hz~10kHz (±3dB)
AUX Frequency Response	100Hz~16kHz (±3dB)
Noise	<10mV
Distortion	<1% 1KHz
Bass Adjustment	10dB
Treble Adjustment	10dB
Rated Output Power	250W
Interface Output Voltage	70V,100V
Machine Dimension (D×W×H)	252×232×67mm

Cannex Technology Inc.

台灣日旭科技

No.182, Sec. 2, Yuanlu Rd., Sihu Town 514, Changhua County, Taiwan Tel:- +886-4-8613883, FAX:-

+886-6-8828209, Email:- sales@amplimic.com.tw

Home Page : <http://www.amplimic.com.tw>